v.LOGiC Intelligent Solution Interface

V6-NTG6-26

Compatible with 7" and 10.25" MBUX systems with 26pin socket in Mercedes vehicles

Product features

- Interactive lane lines with calibration function
- Own on-screen display and setup
- Rear-view camera input
- Automatic switching to rear-view camera input on engagement of reverse gear from all operation modes
- Front camera input
- Side camera inputs
- Side- or front camera activation via blinker signal
- Manual switching to cameras
- 2 trigger outputs (+12V max. 1A), separately adjustable switching events (CAN, ACC, camera, reverse gear)
- Compatible with all factory video accessories
- USB update-port for software-updates by consumer
- Plug&Play installation for MBUX systems with 26 pin socket

Contents

1. Prior to Installation

- 1.1. Delivery contents
- 1.2. Check compatibility of vehicle and accessories
- 1.3. Setting the DIP switches of the interface-box V6C-M626-SP
- 1.4. LED's of the interface-box V6C-M626-SP

2. Connection schema

3. Installation

- 3.1. Connecting interface-box and harnesses on MBUX systems with 26 pin socket
- 3.2. GMSL connection
- 3.2.1. After-market front camera
- 3.2.1.1. Connection to the after-market front camera
- 3.2.1.2. Settings for connecting an after-market front camera
- 3.2.2. After-market wide view front camera
- 3.2.2.1. Connection to the after-market wide view front camera
- 3.2.2.2. Settings for connecting an after-market wide view front camera
- 3.2.3. After-market side view cameras
- 3.2.3.1. Connection of the after-market side view cameras
- 3.2.3.2. Settings for connecting of after-market side view cameras
- 3.2.4. After-market rear-view camera
- 3.2.4.1. Connection to the after-market rear-view camera
- 3.2.4.2. Settings for connecting an after-market rear-view camera
- 3.2.4.3. Settings for OEM rear-view camera
- 3.2.5. Configurable trigger outputs
- 3.3. Interactive lane lines
- 3.3.1. Interactive lane lines settings
- 3.4. Picture settings

4. Operation

- 4.1. Main OSD On-screen display
- 4.1.1. OSD Operation
- 4.1.1.1. Mercedes steering wheel version 1
- 4.1.1.2. Mercedes steering wheel version 2
- 4.1.1.3. Mercedes steering wheel version 3
- 4.1.2. OSD Additional setting options
- 4.2. Selecting the interface as current video source
- 4.2.1. Mercedes steering wheel version 1
- 4.2.2. Mercedes steering wheel version 2

5. Specifications

- 6. Connections (interface-box)
- 7. Technical support

Legal Information

By law, watching moving pictures while driving is prohibited, the driver must not be distracted. We do not accept any liability for material damage or personal injury resulting, directly or indirectly, from installation or operation of this product. This product should only be used while standing or to display fixed menus or rear-view-camera video when the vehicle is moving, for example the MP3 menu for DVD upgrades.

Changes/updates of the vehicle's software can cause malfunctions of the interface. We offer free software-updates for our interfaces for one year after purchase. To receive a free update, the interface must be sent in at own cost. Labor cost for and other expenses involved with the software-updates will not be refunded.

1. Prior to installation

Read the manual prior to installation. Technical knowledge is necessary for installation. The place of installation must be free of moisture and away from heat sources.

1.1. Delivery contents



1.2. Check compatibility of vehicle and accessories

Requirements						
Brand	Compatible vehicles	Compatible systems				
Mercedes	A-Class (W177) since 05/2018 B-Class (W247) since 12/2018 CLA Coupé (C118) since 03/2019 CLA Shooting B (X118) since 07/2019 EQC (N293) since 2019 GLB (X247) since 09/2019 GLC Class (X253) since model year 2019 GLE Coupé (C167) since model year 2019 GLE SUV (W167) since model year 2019 GLS- Class (X166) since model year 2019 Sprinter (W907/910) since model year 2018 V-Class (W447) since model year 2019	MBUX with 26 pin socket: 7" screen <u>with navigation</u> 10.25" screen				

1.3. Setting the DIP switches of the interface-box V6C-M626-SP

DIP switches on the back of the interface-box V6C-M626-SP are used to set the monitor type. The default setting is:

Head unit	DIP 1	DIP 2	DIP 3
7" NTG6 screen	OFF	OFF	OFF
10.25" NTG6 screen	ON	OFF	OFF

After each change of the DIP switch settings you have to execute a power reset of the interface-box!

1.4. LED's of the interface-box V6C-M626-SP





2. Connection scheme





3. Installation

Switch off ignition and disconnect the vehicle's battery! The interface needs a permanent 12V source. If according to factory rules disconnecting the battery is to be avoided, it is usually sufficient to put the vehicle is sleep-mode. In case the sleep-mode does not show success, disconnect the battery with a resistor lead.

If power source is not taken directly from the battery, the connection has to be checked for being start-up proven and permanent.

Prior to wire and device installation we suggest to connect and test correct function of all after-market and factory infotainment equipment!

The interface is installed on the backside of the head unit.

A-Class: On the A-pillar on the driver's side GLE: Under the passenger seat Sprinter: Behind the factory monitor

3.1. Connecting interface box and harnesses on MBUX systems with 26 pin socket



Remove the female 26pin connector of the vehicle harness from the rear of the navigation computer and connect it to the male 26pin socket of the V6C-MBN6-SP harness.

Connect the female 26pin connector of V6C-MBN6-SP harness to the male 26pin socket of the navigation computer.

Connect female 18pin AMP connector of the harness V6C-MBN6-SP to the front site of the V6C-M626-SP interface box.

Connection assignment 26pin head unit connector:

Assignment head unit +12V permanent - Pin 14 (• Red) Ground - Pin 1 (• Brown) CAN HIGH - Pin 7 (• Purple/White) CAN LOW - Pin 20 (• Purple)



26pin head unit connector



3.2. GMSL connection



- 1 Remove the GMSL pink-bordeaux coloured female double Fakra connector of the vehicle harness at the back of the head unit and connect it to the male double Fakra socket (*DISPLAY GMSL*) of the CAB-DFF-YDMF050 GMSL cable.
 - 2 Connect the female double Fakra connector (*HEAD UNIT GMSL*) of the GMSL cable CAB-DFF-YDMF050 to the pink-bordeaux coloured double male Fakra socket on the rear of the head unit.
- 3 Connect the double female Fakra connector (*INTERFACE GMSL*) of the CAB-DFF-YDMF050 GMSL cable to the double male Fakra socket (GMSL) on the rear of the interface box V6C-M626-SP.



3.2.1. After-market front camera

Interface-box V6C-M626-SP FRONT V6C-MBN6-SP harness V4C-VIDEO harness u AV-3 AV-1 AV-2 R-CAM 1 +12V power output 1 (12V OUTPUT 1) 2 Front camera

3.2.1.1. Connection to the after-market front camera

Connect the video RCA of the after-market front camera to the female RCA connector "AV-1" of the V4C-VIDEO harness.

The pink wire (12V OUTPUT 1) of harness V6C-MBN6-SP can be used for +12V electric power supply (max. 1A) of the after-market front camera. Configure in the OSD-menu "Option 1", menu item "Power Out 1" the setting "CAM" (see also chapter "Configurable switching outputs").

V. OGiC	Caraud	io- S ystems
Input Option 1 Option 2 Osd CAN	Park Logic RVC Lines Power Out 1 Power Out 2	Speed_Time DN CAM CAM
Info Exit	Car Type Factory Reset	Others

3.2.1.2. Settings for connecting an after-market front camera

You have to configure some settings in the OSD-menus Inputs, Option 1 and Option 2 if you want to connect an after-market front camera (Operation of the OSD: see chapter "OSD-Operation").

M. OGiC	Caraudio-	S ystems	V OGiC	Caraud	io- <mark>S</mark> ystems	V. OGiC	Caraud	lio-Systems
Input Option 1 Option 2 Osd CAN Info Exit	RVC ON FVC ON Right VC/AV1 ON Left VC/AV2 ON BACK	1	Input Option 1 Option 2 Osd CAN Info Exit	Park Logic RVC Lines Power Out 1 Power Out 2 Car Type Factory Reset Back	Speed_Time ON CAM CAM Others	Input Option 1 Option 2 Osd CAN Info Exit	R/F Cam Till F/S Cam From F/S Cam Till Cam Trigger Blinker Mode Back	10 0 20 Can 0FF

OSD-menu	Menu item	Setting	Explication
		OFF	Front camera deactivated
Input	FVC	ON	Switches to front camera if parking process is enabled and reverse gear is released
		RGearOnly	Enabled while parking process (not suitable for front camera operation)
Option 1	Park Logic	Speed_Time	Enabled while parking process and up to e.g. 10km (speed adjustable) or up to 20 second
Option 2	R/F Cam Till	хх	Speed setting for deactivating of the camera image

Note: You can deactivate the camera image by long pressing the "Back" button on steering wheel (right steering wheel side).

Page

3.2.2. After-market wide view front camera



3.2.2.1. Connection to the after-market wide view front camera

Connect the video RCA of the after-market wide view front camera to the female RCA connector "AV-1" of the V4C-VIDEO harness.

2 The pink wire (12V OUTPUT 1) of harness V6C-MBN6-SP can be used for +12V electric power supply (max. 1A) of the after-market front camera. Configure in the OSD-menu "Option 1", menu item "Power Out 1" the setting "CAM" (see also chapter "Configurable switching outputs").

V. OGiC	Caraudio-Systems			
Input Option 1 Option 2 Osd	Park Logic RVC Lines Power Out 1	Speed_Time DN CAM		
CAN Info	Power Out 2 Car Type	CAM Others		
Exit	Factory Reset Back			

Exception: Connect the white/black wire of harness V6C-MBN6-SP to the right and left analogue blinker signals (triggered +12V blinker power) and make the menu setting - Option 2 / Cam Trigger - "Analogue", if the system doesn't switch to the aftermarket wide view front camera automatically after the described OSD-setup (Option 2 / Cam Trigger - "CAN", see next chapter).



3.2.2.2. Settings for connecting an after-market wide view front camera

For the use of a wide view front camera, the interface offers not only manual activation, but also activation via the blinker function. Note: via CAN bus blinker signal detection (menu: Option 2 / Cam Trigger - "CAN"), the activation does not take place in "blinker comfort mode" (brief touch of the blinker lever).

You have to configure some settings in the OSD-menus Inputs, Option 1 and Option 2 if you want to connect an after-market front camera (Operation of the OSD: see chapter "OSD-Operation").

V. OGiC	Caraudio-	ystems	VOGiC	Caraud	io- <mark>S</mark> ystems	VOGic	Caraud	lio- <mark>S</mark> ystems
Input Option 1 Option 2 Osd CAN Info Exit	RVC ON FVC ON Right VC/AV1 ON Left VC/AV2 ON BACK		Input Option 1 Option 2 Osd CAN Info Exit	Park Logic RVC Lines Power Out 1 Power Out 2 Car Type Factory Reset Back	Speed_Time ON CAM CAM Others	Input Option 1 Option 2 Osd CAN Info Exit	R/F Cam Till F/S Cam From F/S Cam Till Cam Trigger Blinker Mode Back	19 8 28 CAN Front Cam

OSD-menu	Menu item	Setting	Explication
		OFF	Front camera deactivated
Input	FVC	ON	Switches to front camera if parking process is enabled and reverse gear is released
		RGearOnly	Enabled while parking process (not suitable for front camera operation)
Option 1	Park Logic	Speed_Time	Enabled while parking process and up to e.g. 10km (speed adjustable) or up to 20 second
Option 2	R/F Cam Till	хх	Speed setting for deactivating of the camera image
Option 2	F/S Cam From	хх	Speed range setting for front- and side cameras (minimum)
Option 2	F/S Cam Till	хх	Speed range setting for front- and side cameras (maximum)
Option 2	Blinker Mode	Front Cam	Activation of the front camera image when the blinker is activated
Ontion 2	Com Triggor	CAN	Rear gear and blinker signal detection over CAN Bus
Option 2	Cam Trigger	Analogue	Rear gear and blinker signal detection over analogue +12V signals

Notes: The camera activation via the blinker mode is only available for front camera <u>or</u> for the side view cameras. A parallel use of this function for all cameras is not possible.

3.2.3. After-market side view cameras



3.2.3.1. Connection of the after-market side view cameras

Connect the video RCA of the right side view camera to the female RCA connector "AV-2" and the video RCA of the left side view camera to the female RCA connector "AV-3" of the V4C-VIDEO harness.

The pink wire (12V OUTPUT 1) of harness V6C-MBN6-SP can be used for +12V electric power supply (max. 1A) of the after-market side cameras. Configure in the OSD-menu "Option 1", menu item "Power Out 1" the setting "CAM" (see also chapter "Configurable switching outputs").

V OGiC	Caraudio- <mark>S</mark> ystem			
Input Option 1 Option 2 Osd CAN	Park Logic RVC Lines Power Out 1 Power Out 2	Speed_Time DN CAM CAM		
Info Exit	Car Type Factory Reset	Others		

3 Exception: Connect the yellow/red wire to the right analogue blinker signal and the yellow/green wire to the left analogue blinker signal of harness V6C-MBN6-SP (triggered +12V blinker power) and make the menu setting - Option 2 / Cam Trigger - "Analogue", if the system doesn't switch to the aftermarket side view camera automatically after the described OSD-setup (Option 2 / Cam Trigger - "CAN", see next chapter).



3.2.3.2. Settings for connecting of after-market side view cameras

For the use of side view cameras, the interface offers not only manual activation, but also activation via the blinker function. Note: via CAN bus blinker signal detection (menu: Option 2 / Cam Trigger - "CAN"), the activation does not take place in "blinker comfort mode" (brief touch of the blinker lever).

You have to configure some settings in the OSD-menus Inputs, Option 1 and Option 2 if you want to connect an after-market front camera (Operation of the OSD: see chapter "OSD-Operation").

V OGiC	Caraudio-	ystems	VOGiC	Caraud	io- <mark>S</mark> ystems	VOGiC	Caraud	lio- <mark>S</mark> ystems
Input Option 1 Option 2 Osd CAN Info Exit	RVC ON FVC ON Right VC/AV1 ON Left VC/AV2 ON BACK	1	Input Option 1 Option 2 Osd CAN Info Exit	Park Logic RVC Lines Power Out 1 Power Out 2 Car Type Factory Reset Back	Speed_Time ON CAM CAM Others	Input Option 1 Option 2 Osd CAN Info Exit	R/F Can Till F/S Can From F/S Can Till Can Trigger Blinker Mode Back	10 8 20 CAN Side Cam

OSD-menu	Menu item	Setting	Explication
laaut	Right VC	ON	Right camera input activated
input	Left VC	ON	Left camera input activated
		RGearOnly	Enabled while parking process (not suitable for front camera operation)
Option 1	Park Logic	Speed_Time	Enabled while parking process and up to e.g. 10km (speed adjustable) or up to 20 second
Option 2	R/F Cam Till	хх	Speed setting for deactivating of the camera image
Option 2	F/S Cam From	хх	Speed range setting for front- and side cameras (minimum)
Option 2	F/S Cam Till	хх	Speed range setting for front- and side cameras (maximum)
Option 2	Blinker Mode	Side Cam	Activation of the side view cameras image when the blinker is activated
Option 2	Com Triggor	CAN	Rear gear and blinker signal detection over CAN Bus
Option 2	Cam Trigger	Analogue	Rear gear and blinker signal detection over analogue +12V signals

Notes: The camera activation via the blinker mode is only available for front camera <u>or</u> for the side view cameras. A parallel use of this function for all cameras is not possible.

3.2.4. After-market rear-view camera

3.2.4.1. Connection to the after-market rear-view camera



Connect the video RCA of the after-market rear-view camera to the female RCA connector "R-CAM" of the V4C-VIDEO harness.

2 The green wire (12V OUTPUT 2) of harness V6C-MBN6-SP can be used for +12V electric power supply (max. 1A) of the after-market rear-view camera. Configure in the OSD-menu "Option 1", menu item "Power Out 2" the setting "CAM" (see also chapter "Configurable switching outputs").

VOGiC	Caraud	io- S ystems
Input	Park Logic	Speed_Time
Option 1	RVC Lines	ON
Option 2	Power Out 1	CAM
CAN	Power Out 2	CAM
Info	Car Type	Others
Exit	Factory Reset	

3 **Exception**: Connect the white wire of harness V6C-MBN6-SP to analogue rear gear signal (+12V) and make the menu setting - Option 2 / Cam Trigger - "Analogue", if the system doesn't switch to the aftermarket rear-view camera automatically after the described OSD-setup (Option 2 / Cam Trigger - "CAN", see next chapter).



3.2.4.2. Settings for connecting an after-market rear-view camera

You have to configure some settings in the OSD-menus Inputs, Option 1 and Option 2 if you want to connect an after-market rear-view camera (Operation of the OSD: see chapter "OSD-Operation").

M. OGiC	Caraudio	o- <mark>S</mark> ystems	V OGiC	Caraud	lio- <mark>S</mark> ystems	V OGiC	Caraud	lio- <mark>5</mark>	ystems
Input Option 1 Option 2 Osd CAN Info Exit	RVC OF FVC OF Right VC/AV1 OF Left VC/AV2 OF BACK		Input Option 1 Option 2 Osd CAN Info Exit	Park Logic RVC Lines Power Out 1 Power Out 2 Car Type Factory Reset Back	Speed_Time ON CAM CAM Others	Input Option 1 Option 2 Osd CAN Info Exit	R/F Cam Till F/S Cam From F/S Cam Till Cam Trigger Blinker Mode Back	10 0 20 Can OFF	

OSD-menu	Menu item	Setting	Explication
		OFF	Rear-view camera deactivated
Input	RVC	ON	Switches to rear-view camera if reverse gear is engaged or PDC is activate
		RGearOnly	Enabled while parking process (not suitable for front camera operation)
Option 1	Park Logic	Speed_Time	Enabled while parking process and up to e.g. 10km (speed adjustable) or up to 20 second
Option 1	RVC Lines	ON	Interactive lane lines activated
Option 2	R/F Cam Till	хх	Speed setting for deactivating of the camera image
Option 2	Cam Trigger	CAN	Rear gear and blinker signal detection over CAN Bus
Ορτιοπ 2		Analogue	Rear gear and blinker signal detection over analogue +12V signals

Note: You can deactivate the camera image by long pressing the "Back" button on steering wheel (right steering wheel side).

3.2.4.3. Settings for OEM rear-view camera

OSD-menu	Menu item	Setting	Explication
Input	RVC	OEM	If a factory rear-view camera is existing! The interface turns off, if reverse gear is enabled and it displays factory rear-view camera
Option 1	Park Logic	Speed_Time	Enabled while parking process and up to e.g. 10km (speed adjustable) or up to 20 second
Option 2	R/F Cam Till	хх	Speed setting for deactivating of the camera image



3.2.5. Configurable trigger outputs



You can configure the both +12V trigger outputs separately. The pink wire is (12V OUTPUT 1) is Power Out 1 and the green wire is (12V OUTPUT 2) is Power Out 2.

Note: You can configure the both trigger outputs in the OSD-menu Option 1 separately (Operation of the OSD: see chapter "OSD-Operation").

V. OGIC	Caraudio-Systems		
Input Option 1 Option 2 Osd CAN	Park Logic RVC Lines Power Out 1 Power Out 2	Speed_Time DN CAM CAM	
Info	Car Type	Others	
Exit	Factory Reset Back		

OSD-menu	Menu item	Setting	Explication
		CAN	+12V when the interface is on (red LED on)
		ACC	+12V when ignition is on
ODTION	Power Out 1 (pink)	CAM	+12V when camera input is activated (manually or automatically)
OPTION	Power Out 2	RGear	+12V when reverse gear is engaged
	(green)	AVS	+12V when camera / video input was manually activated
		OFF	Trigger output deactivated

Tip: We recommend for all camera modes the power out setting "<u>CAM</u>" and for AV source the power out setting "<u>AVS</u>" or "<u>ACC</u>".



3.3. Interactive lane lines

You have to configure some settings in the OSD menu Option 1 if you want to activate interactive lane lines (Operation of the OSD: see chapter "OSD-Operation").



VOGiC	Caraudio-Systems			
Input Option 1 Option 2 Osd	Park Logic RVC Lines Power Out 1 Power Out 2	Speed_Time ON CAM CAM		
CAN Info Exit	Car Type Factory Reset Back	Others		

OSD-menu	Menu item	Setting	Explication
	RVC Lines Car Type	OFF	Interactive lane lines deactivated
Option 1		ON	Interactive lane lines activated
		Sprinter / Others	Vehicle type selection

3.3.1. Interactive lane lines settings

The height and width of the interactive lane lines can be set in the OSD menu. For this setting you must at first activate the rear-view camera level and push then the **"HOME**" steering wheel button for 3sec. (right steering wheel side) to activate the settings menu. With the **"VOL**" volume steering wheel button you can select the menu point "Line Height" to change the height of the interactive lane lines and with menu point "Line Width" the width of the lines. Over the menu point "Exit" you can leave this settings menu.



3.4. Picture settings

The camera picture settings can be set in the OSD menu. For this setting you must at first activate the camera level and push then the **"HOME**" steering wheel button for 3sec. (right steering wheel side) to activate the settings menu. With the **VOL**" volume steering wheel button you can select and change the "Brightness", "Contrast", "Saturation", Hue" and "Sharpness" menu points. Over the menu point "Exit" you can leave this settings menu.

Note: The picture settings will be retained for every camera input separately.



4. Operation

4.1. Main OSD On-screen display

You can change the basic configurations of the interface in the OSD (on screen display).



4.1.1. OSD – Operation

The OSD menu can be controlled via the following buttons:

4.1.1.1. Mercedes steering wheel version 1





4.1.1.2. Mercedes steering wheel version 2



4.1.1.3. Mercedes steering wheel version 3



4.1.2. OSD – Additional setting options

The following settings in the OSD menus Option 1 and OSD can be configured over and above the described settings in this manual (Operation of the OSD: see chapter "OSD-Operation"):

V OGiC	Caraud	io-Systems	V OGiC	Carau	dio- <mark>S</mark> ystems
Input Option 1 Option 2 Osd CAN Info Exit	Park Logic RVC Lines Power Out 1 Power Out 2 Car Type Factory Reset Back	Speed_Time ON CAM CAM Others	Input Option 1 Option 2 Osd CAN Info Exit	Position X Position Y Size Osd TimeOut Back	10 10 Large 20
VOGiC	Caraud	io- <mark>S</mark> ystems	V OGiC	Carau	dio- S ystems
Input Option 1 Option 2 Osd CAN Info Exit	Bridge speed Back	500kbit	Input Option 1 Option 2 Osd CAN Info Exit	Company Product Version Release Date Back	Ca-s.info VG-NTG6 1.0.0 Apr 25 2019

OSD-menu	Menu item	Setting	Explication
	POS. X	0-xxx	Horizontal position of the OSD
	POS. Y	0-xxx	Vertical position of the OSD
Osd	Size	Small	Small OSD menu windows
	5120	Large	Large OSD menu windows
	Osd TimeOut	2-20	Time setting for automatic OSD shutoff
CAN	Bridge speed		CAN bus connection status
Info	Version	X.XX.XX	Displays the current SW-version
Option 1	Factory Reset		Resetting to factory settings



- 4.2. Selecting the interface as current video source
- 4.2.1. Mercedes steering wheel version 1



Press long "STAR" button to choose the interface as current video source.

Short press "STAR" button switch the video sources (cameras/AV sources). Each short press will switch to the next enabled input. If all inputs are enabled the order would be as follows:

Rear CAM → *Front CAM* → *Right Cam/AV1* → *Left Cam/AV2* → ...

Inputs which are not enabled are skipped.

The exiting of the interface camera/video level is achieved by **long press** of "**STAR**" button.



4.2.2. Mercedes steering wheel version 2

Long press "handsfree mode OFF" respectively long press "right arrow" button to choose the interface as current video source.

Short press "hang-up" button switch the video sources (cameras). Each short press will switch to the next enabled input. If all inputs are enabled the order is:

FRONT CAM \rightarrow REAR CAM \rightarrow ...

Inputs which are not enabled are skipped.

 $P_{age}25$

5. Specifications

Operation voltage	10.5 – 14.8V DC
Stand-by power drain	1mA
Operation power drain	190mA
Power consumption	2,6W
Temperature range	-20°C to +80°C
Weight (box only)	285g
Measurements (box only) B x H x T	141 x 30 x 105 mm

6. Connections (interface-box)



7. Technical Support

Caraudio-Systems Vertriebs GmbH manufacturer/distribution In den Fuchslöchern 3 D-67240 Bobenheim-Roxheim

email support@caraudio-systems.de

Legal disclaimer: Mentioned company and trademarks, as well as product names/codes are registered trademarks [®] of their corresponding legal owners.