

## Legend700

Steering Wheel Control Tech Tip:

## Legend700 Wiring Diagram

BROWN/BLACK MCU-TX(CAN) BROWN MCU-RX(CAN) ORANGE/BLACK WHEEL KEY2 BLUE/BLACK WHEEL KEY1 YELLOW BLACK GND ORANGE ILLUMI RED ACC PINK PARKING GREEN/WHITE REVERSE BLUE/WHITE P.CNTR BLUE P.ANT **GRAY** FRONT R(+) GRAY/BLACK FRONT R(-) PURPLE REAR R(+) PURPLE/BLACK REAR R(-) WHITE FRONT L(+) WHITE/BLACK FRONT L(-) GREEN REAR L(+) GREEN/BLACK REAR L(-)

- 1- Program the Metra SWC module as Radio Type: Boss.
- 2- Wire ORANGE/BLACK to BROWN and BLUE/BLACK to BROWN/WHITE of the 3.5mm adapter included with the ASWC-1.
- 3- Proceed to SWC Program Menu (shown below) to set to your desired configuration.





## Legend700 Setting Menu:

BROWN/WHITE WIRE



## Legend700 SWC Program Menu:

